



CR385X Lug Kits

For Size 7 & 8 Contactors

Caution: Before installing in a nuclear application, determine that the product is intended for such use.

Warning: Disconnect power before installing or servicing.

Description

These lug kits facilitate the wiring of CR385 and CR386 NEMA Size 7 and 8 contactors and starters, CR385X701A is the Size 7 kit. It contains one single lug and one double lug for each pole. The Size 8 kit, CR385X801A contains two double lugs for each pole. Each lug kit contains all the hardware needed for the line or load side of a three pole contactor. Wiring both line and load sides will require two kits.

Assembly

Caution: Remove power before working on equipment.

In order to assure good electrical connections, the contactor terminals and the lugs must be clean. Assemble the lugs using the 1/2-inch bolts, washers and nuts included in the kit, carefully observing the location of each part in the figures at right. Tighten to approximately 500 lb-in torque.

These instructions do not purport to cover all details or variations in equipment nor to provide for every possible contingency to be met in connection with installation, operation, or maintenance. Should further information be desired or should particular problems arise which are not covered sufficiently for the Purchaser's purposes, the matter should be referred to the nearest GE ED&C sales office.

